

Avaya CM - Reset System

Reset 1 Effects:

- Stable calls are preserved
- System links and stable feature and service state data are preserved.
- Error and alarm logs are preserved. And almost all alarms are resolved.
- Transient calls are dropped.
- Remote access and system port logins are dropped.
- Applications links (CDR, AUDIX etc.) are dropped and reestablished.
- MSS activity is aborted.

Reset 2 Effects:

- All system and application links are dropped.
- All calls are dropped.
- Non-translation feature data is lost.
- All hardware components except PNC components are resetted.
- All busied out maintenance objects are released.
- Circuit packs are reinitialized.

Reset 3 effects:

- Same effects as reset 2 plus;
- Emergency transfer is invoked.
- Translations are reloaded from disk or tape.

Reset 4 effects:

- System software is reloaded. (default medium = disk).
- Before the reboot alarm & error logs are saved to disk.
- After reboot alarm & errors logs are reloaded from disk. (Some error information might be incorrect at this moment).

If this reboot fails your SPE will go down.

Reset 5 Effects:

- More extensive diagnostics are performed compared to all previous resets.

Revision #1

Created 4 April 2023 17:14:50 by Cesar Gzz

Updated 4 April 2023 17:15:00 by Cesar Gzz